

LITTLE GENNY

and Little Genny
Emergency
Power Kit (EK)



BRIGGS & STRATTON
ENERGY SOLUTIONS



SPECIFICATIONS

Inverter

Continuous Output Rating	300 Watts (2.6 Amps @ 115 VAC)
AC Output Rating	115 Pure Sine Volts AC
Frequency Rating	60Hz
Output Wave Form	Pure Sine Wave
DC Input Rating	12 Volts DC
Input Voltage Range	11 to 15 Volts DC
Low Battery Shutdown	10 to 11 Volts DC
Over Voltage Shutdown	15 to 16 Volts DC
USB Output Rating	5 Volts DC MAX / 2.4 Amps DC
AC Output Sockets	2 x North American Standard Outlets
Operating / Storage Humidity RH	5 to 95%

Battery

DC Voltage - Nominal	12.8 Volts DC
Amp-Hours	25 Ah
Rated Watt-Hour Capacity	322 Watt-hours DC
Operating Temperature	-4°F to 140°F (-20°C to 60°C)
Charging Temperature	32°F to 120°F (0°C to 49°C)
Battery Chemistry	Lithium Ferro Phosphate (LFP)
Memory Effect	None
Charge Cycles	2,500 cycles
Charging Requirements	14.65 VDC / up to 8 Amps DC

LITTLE GENNY

and Little Genny
Emergency Power Kit (EK)



Little Genny EK's Solar Module (not included with regular Little Genny models)	
Peak Output	80 Watts / 4.44 Amps at 18 VDC
Solar Input	12 to 18 VDC, up to 15A
Folded Dimensions	22" L x 20" W x 0.4" D
Opened Dimensions	22" L x 40" W x 0.2" D
Net Weight	4.8 lbs. / 2.2 kg
Dimensions	
Width (mm)	13" (330.0)
Depth (mm)	7" (180.0)
Height (mm)	11" (280.0)
Weight (kg)	12 lbs (5)



BRIGGS & STRATTON
POST OFFICE BOX 702
MILWAUKEE, WI 53201 USA

Copyright © 2024 Briggs & Stratton. All rights reserved.

All specifications listed are typical/nominal and subject to change without notice.

Engineered in California, USA. Briggs & Stratton has a policy of continuous product improvement and reserves the right to modify its specifications at any time and without prior notice. Please visit energy.briggsandstratton.com for the latest information.

BS1441 - 4/25/24